

CQV2 系列断路器

CQV2 SERIES CIRCUIT BREAKERS

CHAC

CQV2系列电动机保护断路器适用于交流50/60HZ,额定工作电压至690V,电流0.1至80A的电路中,作为三相鼠笼型异步电动机的过载、断相、短路保护及不频繁地起动控制之用,可用作配电线路保护和不频繁的负载转换,还可作隔离器使用。

CQV2 series motor protection circuit breaker is suitable for AC50/60HZ, rated working voltage to 690V, current 0.1 to 80A circuit, as a three-phasesquirrel cage asynchronous motor overload, phase break, short circuit protection and infrequent start control, can be used as distribution line protection and infrequent load conversion, can also be used as an isolator.



主要技术参数 Main Technical Parameters

产品型号 Productmode	额定电流 Rated current (A)	电动机 输出功率 Motor output(kW)	额定电流范围 Setting Range(A)		订货号 Order No.	装箱参数 Packing parameters
CQV2-ME32			热过载脱扣器 Thermal overload releases	瞬时过电流脱扣器 Instantaneous overcurrent releases		QTY:50PCS N.W:13.5KG G.W:15KG MEAS:48X27X19CM
	0.16	0.04	0.1-0.16	1.9	CQV2-ME01	
	0.25	0.07	0.16-0.25	3.0	CQV2-ME02	
	0.4	0.09/0.12	0.25-0.4	4.8	CQV2-ME03	
	0.63	0.12/0.18	0.4-0.63	7.2	CQV2-ME04	
	1	0.25	0.63-1	12	CQV2-ME05	
	1.6	0.37/0.55	1-1.6	19	CQV2-ME06	
	2.5	0.75	1.6-2.5	30	CQV2-ME07	
	4.0	1.1/1.5	2.5-4	51	CQV2-ME08	
	6.3	2.2	4-6.3	78	CQV2-ME10	
	10	3/4	6-10	138	CQV2-ME14	
	14	4/6.5	9-14	170	CQV2-ME16	
	18	7/8	13-18	220	CQV2-ME20	
	23	8/10	17-23	320	CQV2-ME21	
CQV2-ME80	25	9/12	20-25	350	CQV2-ME22	QTY:30PCS N.W:23KG G.W:23.5KG MEAS:42X36X27.7CM
	32	15	24-32	420	CQV2-ME32	
	40	18.5	25-40	480	CQV2-ME40	
CQV2-ME80	63	28	40-63	720	CQV2-ME63	
	80	32	56-80	960	CQV2-ME80	

附加触头 Contacts of accessories




产品型号 Productmode	附件名称 Names of accessories	代号 Code	触类型 The types of contacts	安装位置 Installation place
CQV-AE	瞬时辅助触头 Instantaneousauxiliary contacts	AE1	一常开或一常闭 Constant-open orconstant-closed	断路器前面 The front of breaker
		AE11	一常开一常闭 Constant-open constant-closed	
		AE20	两常开 Two constant-open	
		AN11	一常开一常闭 Constant-open constant-closed	断路器左侧 The left of breaker
		AN20	两常开 Two constant-open	
故障信号触头 Signalcontacts for trouble + 瞬时辅助触头 Instantaneous auxiliary contacts	AD1010	常开(故障) Constant- open trouble	常开 constant-open 常闭 constant-closed 常开 constant-open 常闭 constant-closed	
	AD1001			
	AD0110	常闭(故障) Constant- cosed trouble		
	AD0101			
CQV-AN(-AD-AM)	短路信号触头 Short circuit signal contacts	AM11	常开、常闭 Constant-open、constant-closed	

电脱扣 Electirc disjoining

产品型号 Productmode	附件名称 Names of accessories	代号 Code	电压(V) Voltage	电压要求 (V)	安装位置 Installation place
CQV-AU(-AX-AS)	欠压脱扣 Lack-voltage disjoining	AU115	110-127V50Hz	工作电压： 0.85....1.1Ue 断路电压： 0.35.....0.7Ue	断路器右侧 The right of breaker
		AU225	220-240V 50Hz		
		AU385	380-415V50Hz		
	分励脱扣 Division disjoining	AS115	110-127V50Hz	工作电压： 0.75....1.1Ue 断路电压： 0.2.....0.75Ue	
		AS225	220-240V 50Hz		
		AS385	380-415V 50Hz		
	欠压脱扣(符合INRS) Lack-voltage disjoiningmeets INRS	AX115	110-127V50Hz	工作电压： 0.85....1.1Ue 断路电压： 0.35.....0.7Ue	
		AX225	220-240V50Hz		
		AX385	380-415V50Hz		

CQV2断路器的防护罩 CQV2 Circuit shield

	产品型号 Productmode	应用 Application	类型 Type	外壳保护程度 Shell level of protection	装箱尺寸 Packing size
	CQV2-MC02	用于带或不带附件的CQV2断路器 (最多左右各带1个附件) Used with or without attached Of the circuitbreaker CQV2(With a maximum ofabout Annex 1)	表面安装，双绝缘，可将盖密 封，保护导电部分 Surface mount, Double insulation, Can be covered, sealed and Conducting some protection	IP55	51X31.5X48.5CM

